

ANWENDERINFORMATION - APPLICATION

Parallel-Remote Adapter für Studer A810

Dieser Adapter ermöglicht die Steuerung der Studer A810 (mit RS232 Remote-Zusatz) per Revox Infrarot B202-Empfänger und einem der Standard-Revox-Fernsteuersender B201/205/208.

Gesteuert werden die Funktionen Play, Record, Vorspulen, Rückspulen und Stop.

Da auf den Fernsteuersendern B201/205/208 keine Tasten für "LOC" und "Trans" vorgesehen sind, wird diese Funktion durch eine trickreiche Schaltung über die Pause-Taste der Fernbedienung ermöglicht.

Ca. 2 Sekunden Betätigung der Pause-Taste bewirkt das Setzen des Locator-Speichers, bei kurzem Druck der Pause-Taste wird diese Locator-Position angefahren.

Belegung des D-Sub 25 Steckers:

Pin 1 GND

Pin 4 Key

Pin 6 /TRANS

Pin 18 /LOC1

Pin 19 /REC

Pin 20 /REW

Pin 21 /FF

Pin 22 /PLAY

Pin 23 /STOP

Pin 24 Key

Pin 25 +24V

English:

This adapter is designed for the Studer A810 tape recorder that has a built-in 25-pin parallel remote type remote connector.

These basic functions can be controlled: play, record, fastwind, rewind and stop.

A tricky electronic is built in - deciding how long you have pushed the pause button of the B201/B205/B208 remote sender - setting autolocator memory "Trans" or go to memory pos."Loc1".

Pushing the pause button longer (2 sec) activates function "Trans".

Pushing pause only momentarily - during a short time - activates function "Loc1".